

# KVV-65A-3XKIT



Tri-sector solution that includes 3 KVV-65A-R2-V1 antennas and mounting kit to install them on a pipe

- Suitable for attachment to 3.5-6.6 in or 89-168 mm outer diameter pipe
- Compatible with canister concealment shrouds with inner diameter > 23.5 in (597mm)
- Minimum shroud diameter is the same for all applicable pipe diameters

## General Specifications

Band	Multiband
Performance Note	Outdoor usage
RF Connector Interface	4.3-10 Female
RF Connector Location	Bottom
RF Connector Quantity, mid band	12
RF Connector Quantity, low band	6
RF Connector Quantity, total	18

## Electrical Specifications

Operating Frequency Band	1695 – 2690 MHz   617 – 960 MHz
--------------------------	---------------------------------

## Packaging and Weights

Width, packed	601 mm   23.661 in
Depth, packed	1027 mm   40.433 in
Length, packed	1667 mm   65.63 in
Weight, gross	128.8 kg   283.955 lb

## Regulatory Compliance/Certifications

Agency	Classification
CHINA-ROHS	Below maximum concentration value
REACH-SVHC	Compliant as per SVHC revision on <a href="http://www.commscope.com/ProductCompliance">www.commscope.com/ProductCompliance</a>
ROHS	Compliant
UK-ROHS	Compliant



# KVV-65A-3XKIT

---

\* Footnotes

**Performance Note**      Severe environmental conditions may degrade optimum performance