JAHH-33C-R3B



8-port sector antenna, 2x 698–798, 2x 824-894 and 4x 1695–2360 MHz, 33° HPBW, low bands each have a RET and high bands share a RET. Internal SBT for low band and internal SBT for high band.

- Internal SBT on low and high band allow remote RET control from the radio over the RF jumper cable
- One RET for 700MHz, one RET for 850MHz, and one RET for both high bands to ensure same tilt level for 4x Rx or 4x MIMO
- Internal filter on low band and interleaved dipole technology providing for attractive, low wind load mechanical package
- Separate RS-485 RET input/output for low and high band
- Narrow beamwidth capacity antenna for higher level of densification and enhanced data throughput

General Specifications

Antenna Type Sector

Band Multiband

Grounding Type RF connector body grounded to reflector and mounting bracket

Performance Note

Outdoor usage | Wind loading figures are validated by wind tunnel

measurements described in white paper WP-112534-EN

Radome Material Fiberglass, UV resistant

Radiator Material Aluminum | Low loss circuit board

Reflector Material Aluminum

RF Connector Interface 4.3-10 Female

RF Connector Location Bottom

RF Connector Quantity, high band 4
RF Connector Quantity, mid band 0
RF Connector Quantity, low band 4
RF Connector Quantity, total 8

Remote Electrical Tilt (RET) Information

RET Interface 8-pin DIN Female | 8-pin DIN Male

RET Interface, quantity 2 female | 2 male

Input Voltage 10-30 Vdc

Internal Bias Tee Port 1 | Port 5



Page 1 of 4

JAHH-33C-R3B

Internal RET High band (1) | Low band (2)

Power Consumption, idle state, maximum 1 W

Power Consumption, normal conditions, maximum 8 W

Protocol 3GPP/AISG 2.0 (Single RET)

Dimensions


Length

Width 640 mm | 25.197 in

Depth 235 mm | 9.252 in 2438 mm | 95.984 in

Net Weight, without mounting kit 66 kg | 145.505 lb

Array Layout



Ar	ray	Freq (MHz)	Conns	RET (SRET)	AISG RET UID
F	₹1	698-798	1-2	1	ANxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx
F	₹2	824-894	3-4	2	ANxxxxxxxxxxxxx2
١	/1	1695-2360	5-6	2	ANImanagananagana 2
١	/2	1695-2360	7-8	3	ANxxxxxxxxxxxx3

(Sizes of colored boxes are not true depictions of array sizes)

Port Configuration

Bottom



Electrical Specifications

Impedance 50 ohm

Operating Frequency Band 1695 – 2360 MHz | 698 – 798 MHz | 824 – 894 MHz

Polarization ±45°

Total Input Power, maximum $800 \text{ W} \ \text{@} \ 50 \ ^{\circ}\text{C}$

Electrical Specifications

· ·						
Frequency Band, MHz	698-798	824-894	1695-1880	1850-1990	1920-2200	2300-2360
Gain, dBi	18.3	19	19.8	20.2	20.6	21.4
Beamwidth, Horizontal, degrees	36	32	34	34	33	29
Beamwidth, Vertical, degrees	9.5	8.6	5.8	5.4	5	4.6
Beam Tilt, degrees	0-10	0-10	2-12	2-12	2-12	2-12
Horizontal Sidelobe, dB	21	20	20	18	18	19
USLS (First Lobe), dB	18	21	17	18	18	20
Front-to-Back Ratio at 180°, dB	32	39	35	37	38	36
Isolation, Cross Polarization, dB	25	25	25	25	25	25
Isolation, Inter-band, dB	30	30	30	30	30	30

Page 3 of 4



JAHH-33C-R3B

VSWR Return loss, dB	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0
PIM, 3rd Order, 2 x 20 W, dBc	-153	-153	-153	-153	-153	-153
Input Power per Port at 50°C, maximum, watts	150	150	250	250	250	200

Mechanical Specifications

 Wind Loading @ Velocity, frontal
 954.0 N @ 150 km/h (214.5 lbf @ 150 km/h)

 Wind Loading @ Velocity, lateral
 355.0 N @ 150 km/h (79.8 lbf @ 150 km/h)

 Wind Loading @ Velocity, maximum
 1,434.0 N @ 150 km/h (322.4 lbf @ 150 km/h)

 Wind Loading @ Velocity, rear
 1,086.0 N @ 150 km/h (244.1 lbf @ 150 km/h)

 Wind Speed, maximum
 241 km/h (150 mph)

Packaging and Weights

 Width, packed
 752 mm | 29.606 in

 Depth, packed
 382 mm | 15.039 in

 Length, packed
 2590 mm | 101.969 in

 Weight, gross
 92.7 kg | 204.368 lb

Regulatory Compliance/Certifications

Agency	Classification
CHINA-ROHS	Above maximum concentration value
ISO 9001:2015	Designed, manufactured and/or distributed under this quality management system
ROHS	Compliant/Exempted
UK-ROHS	Compliant/Exempted



Included Products

BSAMNT-4 - Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members.

Kit contains one scissor top bracket set and one bottom bracket set.

BSAMNT-M4 - Middle Downtilt Mounting Kit for Long Antennas for 2.4 - 4.5 in (60 - 115 mm) OD round

members. Kit contains one scissor bracket set.

* Footnotes

Performance Note Severe environmental conditions may degrade optimum performance

