# Installation Instructions

**COMMSCOPE**®

### MT500B-KIT-ELMNT MT500B DEHYDRATOR FILTER ELEMENT REPLACEMENT KIT

.01 Micron Filter Marked with the number 4 qty 2





1.0 Micron Filter Marked with the number 12 qty 2

#### ANDREW FILTER ELEMENT KIT COMPONENTS See product O & M Manual for additional detail



- 1. Remove the front panel and top panel of the MT500B.
- 2. For the Durr-Teknik air compressor (finned compressor head) remove and replace the entire filler housing.
- 3. For the GAST air compressor, (smooth compressor head) remove the outer part of the filter housing and replace the felt filter, or replace the entire filter housing.
- 4. The filter bowls can be removed with a strap wrench or very carefully with a large wrench through the front opening of the unit.
- Replace the filter elements on the left hand side with the filter element marked with the number "12" and the filter element marked with the number "4" goes on the right hand side as you face the unit.





## MT500B-KIT-ELMNT

**MT500B DEHYDRATOR FILTER ELEMENT REPLACEMENT KIT** 



# COMMSCOPE<sup>®</sup> One Company. A World of Solutions.

3 Westbrook Corporate Center Suite 900 Westchester, IL 60154 USA

**Customer Support Center** From North America Telephone: 1-800-255-1479

International Telephone: +1-779-435-6500

Internet: www.andrew.com

All designs, specifications and availability of products and services presented in this bulletin are subject to change without notice.

Bulletin AE01B-A0531-002 (3/11) © 2007 - 2011 Andrew L.L.C., All rights reserved Andrew Corporation, 3 Westbrook Corporate Center, Suite 900 Westchester, IL 60154 USA