# NNHH-65B-R4N17



# 8-port sector antenna, 4x 694–896 and 4x 1695–2360 MHz, 65° HPBW, 4x RETs

- Array configuration provides capability for 4T4R (4x MIMO) on Low band and High band
- Optimized SPR performance across all operating bands
- Excellent wind loading characteristics

#### Alternative products available:

8P-4L4M-B4

8-port sector antenna, 4x 694–960 and 4x 1695–2690 MHz, 65°HPBW, 4x RET

## General Specifications

BandMultibandColorLigh Gray (RAL 7035)Grounding TypeRF connector inner conductor and body grounded to reflector and mounting bracketPerformance NoteOutdoor usageRadome MaterialFiberglass, UV resistantRadiator MaterialAluminumReflector MaterialAluminumRF Connector InterfaceBottomRF Connector Quantity, high bandAlRF Connector Quantity, numberAlRF Connector Quantity, numberBitRF Connector Quantity, hordBitRF Connector Quantity, hordBitBr Connector Quantity, hordBit <th>Antenna Type</th> <th>Sector</th>	Antenna Type	Sector
Grounding TypeRF connector inner conductor and body grounded to reflector and mounting bracketPerformance NoteOutdoor usageRadome MaterialFiberglass, UV resistantRadiator MaterialLow loss circuit boardReflector MaterialAluminumRF Connector Interface8ottomRF Connector LocationBottomRF Connector Quantity, high band0RF Connector Quantity, mid band0RF Connector Quantity, low band4	Band	Multiband
bracketPerformance NoteOutdoor usageRadome MaterialFiberglass, UV resistantRadiator MaterialLow loss circuit boardReflector MaterialAluminumReflector Interface4.3-10 FemaleRF Connector LocationBottomRF Connector Quantity, high band0RF Connector Quantity, mid band0RF Connector Quantity, neglection4.3-10 FemaleRF Connector Quantity, mid band0RF Connector Quantity, neglection4.3-10 FemaleRF Connector Quantity, neglection4.3-10 FemaleRF Connector Quantity, neglection0RF Connector Quantity, neglection<	Color	Light Gray (RAL 7035)
Radome MaterialFiberglass, UV resistantRadiator MaterialLow loss circuit boardReflector MaterialAluminumRF Connector Interface4.3-10 FemaleRF Connector LocationBottomRF Connector Quantity, high band4RF Connector Quantity, mid band0RF Connector Quantity, low band4	Grounding Type	
Radiator MaterialLow loss circuit boardReflector MaterialAluminumRF Connector Interface4.3-10 FemaleRF Connector LocationBottomRF Connector Quantity, high band4RF Connector Quantity, mid band0RF Connector Quantity, now band4RF Connector Quantity, now band4	Performance Note	Outdoor usage
Reflector MaterialAluminumRF Connector Interface4.3-10 FemaleRF Connector LocationBottomRF Connector Quantity, high band4RF Connector Quantity, mid band0RF Connector Quantity, number band4RF Connector Quantity, number band0RF Connector Quantity, low band4	Radome Material	Fiberglass, UV resistant
RF Connector Interface4.3-10 FemaleRF Connector LocationBottomRF Connector Quantity, high band4RF Connector Quantity, mid band0RF Connector Quantity, mid band4RF Connector Quantity, band0RF Connector Quantity, low band4	Radiator Material	Low loss circuit board
RF Connector LocationBottomRF Connector Quantity, high band4RF Connector Quantity, mid band0RF Connector Quantity, low band4	Reflector Material	Aluminum
RF Connector Quantity, high band4RF Connector Quantity, mid band0RF Connector Quantity, low band4	RF Connector Interface	4.3-10 Female
RF Connector Quantity, mid band 0   RF Connector Quantity, low band 4	RF Connector Location	Bottom
RF Connector Quantity, low band 4	RF Connector Quantity, high band	4
	RF Connector Quantity, mid band	0
RF Connector Quantity, total 8	RF Connector Quantity, low band	4
	RF Connector Quantity, total	8

### Remote Electrical Tilt (RET) Information

RET Hardware	CommRET v2
RET Interface	8-pin DIN Female   8-pin DIN Male
RET Interface, quantity	1 female   1 male
Input Voltage	10-30 Vdc

Page 1 of 4




©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: May 29, 2025

# NNHH-65B-R4N17

Internal RET	High band (2)   Low band (2)
Power Consumption, active state, maximum	10 W
Power Consumption, idle state, maximum	2 W
Protocol	3GPP/AISG 2.0 (Multi-RET)
Dimensions	
Width	430 mm   16.929 in
Depth	197 mm   7.756 in
Length	1848 mm   72.756 in
Net Weight, without mounting kit	28.4 kg   62.611 lb

# Array Layout



Array ID	Frequency (MHz)	RF Connector	RET (MRET)	AISG RET UID
R1	694-896	1 - 2	1	CPxxxxxxxxxxXMM.1
R2	694-896	3 - 4	2	CPxxxxxxxxxxXMM.2
¥1	1695-2360	5 - 6	3	CPxxxxxxxxxxXMM.3
Y2	1695-2360	7 - 8	4	CPxxxxxxxxxxXMM.4

(Sizes of colored boxes are not true depictions of array sizes)

# Port Configuration

Page 2 of 4



©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: May 29, 2025



# Electrical Specifications

Impedance	50 ohm
Operating Frequency Band	1695 – 2360 MHz   694 – 896 MHz
Polarization	±45°
Total Input Power, maximum	900 W @ 50 °C

# **Electrical Specifications**

Frequency Band, MHz	694-806	806-896	1695-1880	1850-1990	1920-2180	2300-2360
Gain, dBi	13.9	14.6	16.6	17.2	17.6	18.2
Beamwidth, Horizontal, degrees	61	57	65	65	63	59
Beamwidth, Vertical, degrees	12.5	10.9	7	6.6	6.2	5.6
Beam Tilt, degrees	2-14	2-14	2-12	2-12	2-12	2-12
USLS (First Lobe), dB	21	18	15	14	14	14
Front-to-Back Ratio at 180°, dB	30	31	32	35	33	31
Isolation, Cross Polarization, dB	25	25	25	25	25	25
Isolation, Inter-band, dB	25	25	25	25	25	25

©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: May 29, 2025





# NNHH-65B-R4N17

VSWR   Return loss, dB	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0	1.5   14.0
PIM, 3rd Order, 2 x 20 W, dBc	-150	-150	-150	-150	-150	-150
Input Power per Port at 50°C, maximum, watts	300	300	250	250	250	200

## Mechanical Specifications

Wind Loading @ Velocity, frontal	471.0 N @ 150 km/h (105.9 lbf @ 150 km/h)
Wind Loading @ Velocity, lateral	241.0 N @ 150 km/h (54.2 lbf @ 150 km/h)
Wind Loading @ Velocity, maximum	762.0 N @ 150 km/h (171.3 lbf @ 150 km/h)
Wind Loading @ Velocity, rear	444.0 N @ 150 km/h (99.8 lbf @ 150 km/h)
Wind Speed, maximum	241 km/h (150 mph)

### Packaging and Weights

Width, packed	530 mm   20.866 in
Depth, packed	349 mm   13.74 in
Length, packed	2020 mm   79.528 in
Weight, gross	41.1 kg   90.61 lb

### Regulatory Compliance/Certifications

Agency	Classification
CHINA-ROHS	Below maximum concentration value
ISO 9001:2015	Designed, manufactured and/or distributed under this quality management system
REACH-SVHC	Compliant as per SVHC revision on www.commscope.com/ProductCompliance
ROHS	Compliant
UK-ROHS	Compliant



#### Included Products

BSAMNT-3

Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.

### \* Footnotes

Performance Note

Severe environmental conditions may degrade optimum performance



©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: May 29, 2025

Page 4 of 4