

16-port sector/multibeam antenna 4x 694–960 MHz , 4x 1695-2690 MHz 65° HPBW and 8x 1710–2690 MHz 2x 2-Beam 33°HPBW, 8x RET. Band cascaded SRET

### General Specifications

Antenna Type	Multibeam
Band	Multiband
Color	Light Gray (RAL 7035)
Grounding Type	RF connector inner conductor and body grounded to reflector and mounting bracket
Performance Note	Outdoor usage   Wind loading figures are validated by wind tunnel measurements described in EN1991-1-4 standard
Radome Material	Fiberglass, UV resistant
Reflector Material	Aluminum
RF Connector Interface	4.3-10 Female
RF Connector Location	Bottom
RF Connector Quantity, high band	12
RF Connector Quantity, mid band	0
RF Connector Quantity, low band	4
RF Connector Quantity, total	16

#### Remote Electrical Tilt (RET) Information

RET Hardware	CommRET v2
RET Interface	8-pin DIN Female   8-pin DIN Male
RET Interface, quantity	2 female   2 male
Input Voltage	10-30 Vdc
Internal RET	High band (6)   Low band (2)
Power Consumption, active state, maximum	8 W
Power Consumption, idle state, maximum	1 W
Protocol	3GPP/AISG 2.0 (Single RET)

#### Dimensions

Page 1 of 5



©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: March 12, 2025

Width	498 mm   19.606 in
Depth	197 mm   7.756 in
Length	2577 mm   101.457 in
Net Weight, antenna only	53 kg   116.845 lb

## Array Layout



Array ID	Frequency (MHz)	RF Connector	HPBW	RET (SRET)	AISG No.	AISG RET UID
R1	694-960	1 - 2	65°	1	AISG1	CPxxxxxxxxxxxxxR1
R2	694-960	3 - 4	65°	2	AISG1	CPxxxxxxxxxxxxxxR2
Y1	1695-2690	5 - 6	65°	3	AISG1	CPxxxxxxxxxxxxxXXXXXXXXXXXXXXXXXXXXXXXX
Y2	1710-2690	7 - 8	33°	4	AISG1	CPxxxxxxxxxxxxxXXXXXXXXXY2
Y3	1710-2690	9 - 10	33°	5	AISG1	CPxxxxxxxxxxxxxXXXXXXXXXXXXXXXXXXXXXXXX
Y4	1710-2690	11 - 12	33°	6	AISG1	CPxxxxxxxxxxxxxXXXXXXY4
Y5	1710-2690	13 - 14	33°	7	AISG1	CPxxxxxxxxxxxxxxXY5
Y6	1695-2690	15 - 16	65°	8	AISG1	CPxxxxxxxxxxxxXXXXXY6

(Sizes of colored boxes are not true depictions of array sizes)

## Port Configuration





©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: March 12, 2025

Page 2 of 5

### **Electrical Specifications**

Impedance	50 ohm
Operating Frequency Band	1695 – 2690 MHz   1710 – 2690 MHz   694 – 960 MHz
Polarization	±45°
Total Input Power, maximum	1,700 W @ 50 °C

### **Electrical Specifications**

Frequency Band, MHz	694-80	6790-89	6890-96	01695-199	01920-230	02300-250	02490-269	01710-199	01920-230	02300-250	02490-2690
Gain at Mid Tilt, dBi	15.3	15.7	15.9	16.7	17.8	18.5	18.6	17.5	18.9	18.9	19.3
Beam Centers, Horizontal, degrees								±27	±27	±27	±27
Beamwidth, Horizontal, degrees	71	64	63	73	64	58	56	36	33	30	27
Beamwidth, Vertical, degrees	9.2	8.2	7.6	5.8	5.3	4.8	4.6	7.2	6.5	5.7	5.3
Beam Tilt, degrees	2-12	2-12	2-12	2-12	2-12	2-12	2-12	2-12	2-12	2-12	2-12
USLS (First Lobe), dB	19	17	18	25	24	21	18	17	19	20	20
Front-to- Back Ratio at 180°, dB	29	28	29	34	33	35	33	38	38	34	32
Front-to- Back Total Power at 180° ± 30°, dB	22	22	22	24	25	28	26	32	31	28	27
CPR at Boresight, dB	24	22	17	21	21	23	22	17	21	17	21
CPR at Sector, dB	10	10	13	8	7	9	7				
Isolation, Cross Polarization,	25	25	25	25	25	25	25	25	25	25	25

ANDREW an Amphenol company

©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: March 12, 2025

dB											
lsolation, Inter-band, dB	25	25	25	25	25	25	25	25	25	25	25
lsolation, Beam to Beam, dB								17	17	17	17
VSWR   Return loss, dB	1.5 14.0	1.5   14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0	1.5 14.0
PIM, 3rd Order, 2 x 20 W, dBc	-150	-150	-150	-150	-150	-150	-150	-150	-150	-150	-150
Input Power per Port at 50°C, maximum,	250	250	250	200	200	200	200	200	200	200	200

### Mechanical Specifications

watts

Wind Loading @ Velocity, frontal	876.0 N @ 150 km/h (196.9 lbf @ 150 km/h)
Wind Loading @ Velocity, lateral	229.0 N @ 150 km/h (51.5 lbf @ 150 km/h)
Wind Loading @ Velocity, maximum	1,165.0 N @ 150 km/h (261.9 lbf @ 150 km/h)
Wind Loading @ Velocity, rear	603.0 N @ 150 km/h (135.6 lbf @ 150 km/h)
Wind Speed, maximum	241 km/h (150 mph)

### Packaging and Weights

Width, packed	565 mm   22.244 in
Depth, packed	309 mm   12.165 in
Length, packed	2824 mm   111.181 in
Weight, gross	74 kg   163.142 lb

#### Regulatory Compliance/Certifications

Agency	Classification
CHINA-ROHS	Below maximum concentration value
ISO 9001:2015	Designed, manufactured and/or distributed under this quality management system
REACH-SVHC	Compliant as per SVHC revision on www.andrew.com/ProductCompliance
ROHS	Compliant
UK-ROHS	Compliant



Page 4 of 5

©2025 ANDREW, an Amphenol company. All rights reserved. Amphenol and ANDREW are registered trademarks of Amphenol and/or its affiliates in the U.S. and other countries. All product names, trademarks and registered trademarks are property of their respective owners. Revised: March 12, 2025



#### Included Products

BSAMNT-4	-	Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.
BSAMNT-M4	_	Middle Downtilt Mounting Kit for Long Antennas for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor bracket set.

### \* Footnotes

Performance Note Severe environmental conditions may degrade optimum performance

