COMMSCOPE[®]

Installation Instructions

TC-1540-IP Rev. B, June 2023

NOVUX™ Fiber Optic System NVX-CR-EX-NN-CC2: External drop cable guidance bracket

Applicable for CC 150/200

1 Kit contents





N°	Description
1	External drop cable guidance bracket
2	Cable ties

2

Install external drop cable guidance bracket



- 1 Front side (drop side) facing forward, slide the external drop cable guidance bracket over the stud.
- 2 The snap feature on the bracket snaps behind the stud.
- 3 4 external drop cable guidance brackets installed.
- **Note:** Maximum mountable brackets on the CC 150 organizer is 4. Maximum mountable brackets on the CC 200 organizer is 6.
- **Note:** Only applicable for drop cables.

All trademarks identified by [®] are registered trademarks in the US and may be registered in other countries. All third party product names, trademarks are property of their respective owners. This product may be covered by one or more U.S. patents or their foreign equivalents. For patents, see www.cs-pat.com. This document is not intended to modify or supplement any specifications or warranties relating to CommScope products or services. Visit our website or contact your local CommScope[®] representative for more information. www.commscope.com. For technical assistance, customer service, or to report any missing/damaged parts, visit us at: http://www.commscope.com/SupportCenter.

Secure single layer drops



1 Guide the cables in the external drop cable guidance bracket and attach with a cable tie as shown.



1 Guide the cables in the external drop cable guidance bracket and attach with a cable tie as shown.

4